

## Tender text

### PA-1414MX

#### 10-channel PA preamplifier

- 5 XLR input channels, switchable mic/line
- 4 input channels, switchable XLR mic/RCA line
- 2 XLR master outputs
- 1 record output (master1, master2)
- Input channels with level control and output selector switch (master1, master1+2, master2)
- Each master output with 2-way tone control
- Chime button with priority circuit, remote control possible, 2-tone chime or 4-tone chime, siren (selectable)
- 1 push-to-talk connection, RJ45, with priority circuit (suitable for PA-4000PTT)
- Low cut filter can be activated as required for each microphone input
- Priority circuit for channels 2-3
- Phantom power for electret microphones can be activated as required for each XLR input channel
- Mains operation or 24 V emergency power operation

#### Specifications:

Output impedance	
Channels	10
Inputs	2.5 mV, bal. (mic), 250 mV, bal. (line XLR), 250 mV, unbal. (line RCA)
Attenuation factor	
Frequency range	20-20,000 Hz (-0.5 dB)
Equalizer bass	± 10 dB/100 Hz
Equalizer treble	± 10 dB/10 kHz
S/N ratio	> 60 dB (mic), > 75 dB (line)
THD	< 0.05%
Mains voltage	~ 230 V
Mains frequency	50 Hz
Power consumption, operation	15 VA
Operating voltage (possible alternative)	DC 24 V
Power supply (possible alternative)	DC 0.5 A
Admiss. ambient temp.	0-40 °C
Width	482 mm
Height	45 mm
Depth	240 mm
Rack spaces, RS	1
Weight	2.5 kg
Connections	9 x XLR (mic/line inputs), 4 x RCA L/R (line inputs), 1 x RJ45 (push-to-talk microphone), 2 x XLR (outputs), 1 x RCA L/R (record output)

Brand: MONACOR

Type: PA-1414MX

Quantity: 1

Packing dimensions (W x H x L): 0.34 x 0.14 x 0.55 m

Gross weight: 3.61 kg

Net weight: 2.57 kg

Item weight (w/o accessories): 2.5 kg