



## PA-1120

Order No.: 0170780

### PRODUCTINFOS

#### 5-zone mono PA mixing amplifier

- 1 x 120 W
- 5 zones, can be controlled individually
- Chime, continuous sound and wailing sound, automatic mute, 2-tone chime or 4-tone chime (selectable)
- Bass, treble and master controls, level display via LEDs, regulated fan
- Insertions for various functions are available at option
- 17 V phantom power for electret microphones
- Connection for zone paging microphone PA-1120RC (available at option)
- Connection for push-to-talk microphone PA-4000PTT or PA-4300PTT
- Automatic alarm announcement with insertion PA-1120DMT (available at option)
- Mains operation and 24 V emergency power operation
- Removable mounting brackets

#### Manufacturer information:

MONACOR INTERNATIONAL GmbH & Co. KG  
Konsul-Smidt-Str. 68  
28217 Bremen  
Germany  
info@monacor.com

## Safety Notes and Warning Messages

The unit uses dangerous mains voltage. Leave servicing to skilled personnel only and do not insert anything into the air vents. Inexpert handling may result in electric shock.

During operation, there may be a hazard of contact with a dangerous voltage of up to 100 V at the speaker terminals. Always switch off the amplifier before making or changing any connections.

Do not operate the unit and disconnect the mains plug from the socket immediately if the unit or the mains cable is visibly damaged; if a defect might have occurred after the unit was dropped or suffered a similar accident, if malfunctions occur. In any case, the unit must be repaired by skilled personnel.

The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).

Never pull the mains cable to disconnect the mains plug from the socket, always seize the plug.

The heat generated inside the unit must be dissipated by air circulation; never cover the air vents of the housing.

If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

## TECHNICAL SPECIFICATIONS

### PA-1120

Peak output power	170 W
Power rating	120 W
Power rating at 4 Ω	120 W
Power rating at 100 V	120 W
Channels	5
Zones	5
Inputs	2.5 mV/5 kΩ, 0.3 V/5 kΩ (mic/line), 0.3 V/15 kΩ (line), 0.775 V/10 kΩ (preamplifier)
Frequency range	55-16,000 Hz
Equalizer bass	± 10 dB/100 Hz
Equalizer treble	± 10 dB/10 kHz
S/N ratio	> 70 dBA (mic), > 80 dBA (line)
THD	< 1%
Phantom power	17 V
Power supply	~ 230 V/50 Hz/340 VA, DC 24 V/15 A
Mains voltage	~ 230 V
Mains frequency	50 Hz
Power consumption, operation	340 VA

**PA-1120**

Operating voltage (possible alternative)	DC 24 V
Power supply (possible alternative)	DC 15 A
Admiss. ambient temp.	0-40 °C
Width	482 mm
Height	133 mm
Depth	352 mm
Rack units, RU	3
Weight	13 kg
Connections	3 x combo 6.3 mm/XLR (mic/line inputs), 2 x RCA L/R (line inputs), 2 x RJ45 (push-to-talk mic), screw contacts (telephone system), 1 x 6.3 mm jack (preamplifier), 1 x 6.3 mm jack (ext. amplifier), 1 x RCA L/R (record), screw contacts (speakers)
Packaging dimensions (W x H x L)	0.48 x 0.22 x 0.54 m
Gross weight	16.5 kg
Net weight	14.52 kg
<b>PA-1120</b>	
EAN code	4007754143126
Net weight	14.52 kg