



## UR-2Q



Order No.: 1001174

### PRODUCTINFOS

#### 4-channel diversity UHF PLL wideband receiver,

with Dante® audio output.

- For sophisticated nightclubs, multi-purpose halls, hotels, conferences and small to medium-sized performances
- Carrier frequency: 470-600 MHz
- Bandwidth: 130 MHz
- SYNC function for synchronising receiver with transmitter
- Auto-scan function (AFS)
- 6 different audio equalizers (Magic EQ)
- OLED status indication for channel or frequency, name of receiver, battery status of the transmitters
- LED for indicating RF signal strength and AF signal strength, antenna A/B
- Removable antennas (BNC connection), with 12 V supply voltage for active antennas or antenna boosters
- XLR output per channel (bal.)
- XLR output (bal.) for mixed signal
- 482 mm (19") rack installation, 1 RU

**There are restrictions or requirements within the EU!**

**Please read the notes regarding wireless systems in the section “IMPORTANT INFORMATION”!**

**Please note: RELACART products are distributed by MONACOR INTERNATIONAL exclusively in the following countries: Germany, Austria, Switzerland, Netherlands, Belgium, Luxembourg, Denmark, Portugal, Malta. Orders from other countries cannot be fulfilled.**

**Manufacturer information:**

Relacart Electronics Co., Ltd.  
1408 Room, B Building  
Fengxing Plaza  
No. 242, Tianhe Road  
Tianhe District  
Guangzhou, Guangdong  
China  
info@relacart.com

**Importer:**

MONACOR INTERNATIONAL GmbH & Co. KG  
Konsul-Smidt-Str. 68  
28217 Bremen  
Germany  
info@monacor.com

**Safety Notes and Warning Messages**

The unit uses dangerous mains voltage. Leave servicing to skilled personnel only and do not insert anything into the air vents. Inexpert handling may result in electric shock.

Do not operate the unit and disconnect the mains plug from the socket immediately if the unit or the mains cable is visibly damaged; if a defect might have occurred after the unit was dropped or suffered a similar accident, if malfunctions occur. In any case, the unit must be repaired by skilled personnel.

The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).

Never pull the mains cable to disconnect the mains plug from the socket, always seize the plug.

If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

**TECHNICAL SPECIFICATIONS**

## **UR-2Q**

### **General information**

Description	receiver unit
Carrier frequency range	470-600 MHz
Audio frequency range	80-18,000 Hz
Channels	4
THD	< 0.7%

### **Specifications transmitter**

#### **Specifications receiver**

Power supply receiver	~ 110-240 V/50-60 Hz/45 W
Width receiver	480 mm
Height receiver	43 mm
Depth receiver	350 mm
Weight receiver	3.93 kg
Connections receiver	5 x XLR, bal., 1 x RJ45 (Dante®)

## **UR-2Q**

EAN code	4007754426588
Net weight	3.93 kg