



FGA-22S

Order No.: 06.7550

Price upon request

PRODUCTINFOS

Transformer with switching voltage generation,

for car radios only, for connecting speaker outputs of a car radio to the line inputs of an amplifier.

- For operation with car audio systems which do not feature a switching voltage output
- Switching voltage (REM) is generated independently of the audio signal, even when the music stops
- Internal ground separation
- Screw terminals, gold-plated RCA jacks
- Max. input power: 20 W
- Input/output impedance: 20 k Ω /10 k Ω
- Frequency range: 20-30,000 Hz
- THD: < 0.01%
- Power supply: DC 12 V/25 mA
- 43 x 27 x 100 mm, 70 g

TECHNICAL SPECIFICATIONS

FGA-22S

Description	transformer
Frequency range	20-30,000 Hz
Input impedance	20 k Ω
Output impedance	10 k Ω
THD	< 0.01%
Admiss. ambient temp.	0-40 °C
Power supply	DC 12 V/25 mA
Dimensions	43 x 27 x 100 mm
Weight	60 g
Inputs	screw terminals
Outputs	1 x RCA L/R