



## NTE-1

Order No.: 0212370

### PRODUCTINFOS

**Audio transformer 1:1 for microphone signals,**

from NEUTRIK.

- Very compact design, e.g. also suitable for installation into connector housings
- Unshielded version with bare wire connections (70 mm)
- Wideband version
- Balance adjustment
- Galvanic isolation to avoid/eliminate hum loops
- Max. input voltage: 550 mV (1% THD/50 Hz)

When installing unshielded transformers into units with interference fields (e.g. power transformers), attention has to be paid to respective shielding measures.

### TECHNICAL SPECIFICATIONS

#### NTE-1

Description

transformer

**NTE-1**

Frequency range	20-20,000 Hz
Input signal	50 mV
Input impedance	200 $\Omega$
Output impedance	2 k $\Omega$
Transmission ratio	1:1
Dimensions	14 x 11 x 12 mm (w/o cable)
Weight	6 g

**NTE-1**

Width	14 mm
Height	11 mm
Depth	12 mm
Weight	6.1 g