

SA-130DMP

Order No.: 0257760

PRODUCTINFOS

Stereo mixing amplifier, 130 W,

with integrated MP3 player, Bluetooth receiver, FM radio and USB port.

- Bluetooth receiver for wireless connection of laptops, smartphones or tablet PCs
- USB storage media can be connected directly
- For SD/MMC cards up to 64 GB (FAT16/FAT32), not included in the scope of delivery
- Adjustable microphone input and aux input on the front panel
- Adjustable stereo line input
- Insert facility, e.g. for effect units, equalizers, feedback controllers
- 2-way tone control
- Adjustable master output
- 482 mm (19") rack installation, 1 RU

TECHNICAL SPECIFICATIONS

SA-130DMP	
Power rating	130 W
Power rating at 4 Ω	2 x 75 W
Power rating at 8 Ω	2 x 45 W
Channels	2
Inputs	600 mV/30 kΩ (line) 2 mV/0.5 kΩ (mic) 370 mV/30 kΩ (aux) 950 mV/25 kΩ (amp in)
Frequency range	20-20,000 Hz

SA-130DMP

Equalizer bass	± 10 dB/100 Hz
Equalizer treble	± 10 dB/10 kHz
S/N ratio	≥ 80 dB
Crosstalk attenuation	≥ 45 dB
THD	≤ 0.1%
Mains voltage	~ 230 V
Mains frequency	50 Hz
Power consumption, operation	320 VA
Admiss. ambient temp.	0-40 °C
Width	482 mm
Height	44 mm
Depth	245 mm
Rack units, RU	1
Weight	5.62 kg
Connections	1 x RCA L/R (line), 1 x XLR/6.3 mm jack (mic), 1 x 3.5 mm jack (aux), 1 x RCA L/R (amp in), 1 x RCA L/R (amp out), screw terminals (speakers) with 4 mm banana jack
Packing dimensions (W x H x L)	0.3 x 0.11 x 0.53 m
Gross weight	6.42 kg
Net weight	5.85 kg