[Ausschreibung]

MA-100/15

Microphone matching transformer,

with Hi/Lo switch. With balanced XLR connection as well as 6.3 mm plug, unbalanced, with 15 cm microphone cable.

• Frequency range: 50-15,000 Hz
• Input impedance: 600 Ω
• Transformation ratio: 1:10/1:1 (1 kHz)

[Technische Daten]:

Type	Microphone matching transformer
Nominal value	50-15,000 Hz, 600 Ω
Type	with Hi/Lo switch
Colour	chrome/black
Weight	80 g
Connections	1 x XLR, bal. 1 x 6.3 mm plug, unbal.
Other features	transformation ratio: 1:10/1:1 (1 kHz)
Sales unit	1

Brand: MONACOR

Type: MA-100/15

Quantity: 1

Packing dimensions: