[Ausschreibung]

FM-102DAB

Digital stereo tuner for reception of FM and DAB+

• FM radio reception (87.5-108 MHz) with RDS function
• Reception of interference-free digital radio via digital audio broadcasting (DAB+, band III, 174.928-239.2 MHz)
• Display of additional broadcasting information, e.g. frequency, name of radio station, genre, track name, artist
• Large backlit dot matrix display
• Field intensity display
• 20 station presets each for FM mode and DAB mode
• 10 station keys with double assignment
• Manual frequency adjustment and station adjustment
• Automatic station scanning
• Mono/stereo selection
• Sleep mode
• 75 Ω antenna input
• Supplied with infrared remote control and telescopic antenna
• 482 mm (19") rack installation, 1 RS, removable mounting brackets

[Technische Daten]:

Type	Digital stereo tuner
Media	FM, DAB+
Power supply	~ 230 V/50 Hz/50 VA
Mains voltage	~ 230 V
Mains frequency	50 Hz
Power consumption, operation	50 VA
Admiss. ambient temp.	0-40 °C
Dimensions	482 x 44 x 185 mm
Weight	2.7 kg
Connections	1 x RCA L/R

Brand: MONACOR

Type: FM-102DAB

Quantity: 1

Packing dimensions: