


**MMA-130**


Order No. 1000236


**8Ω****4Ω****NEW****Mono class D PA mixing amplifier, 30 W/8 Ω.**


- 1 microphone input and 1 line input, adjustable
- Line input each on the front panel and rear panel
- Bass and treble controls
- Mute switch
- LED indication for mute and operation
- Standard mounting dimensions (suitable for slots in motor vehicles)
- Power supply: = 12-24 V

Model	MMA-130
Power rating at 4 Ω	15 W
Power rating at 8 Ω	30 W
Inputs	1.9 mV/560 Ω (mic), 220 mV/4.8 kΩ (line)
Frequency range	20-20,000 Hz
Equalizer bass	± 12 dB
Equalizer treble	± 12 dB
THD	< 0.11%
Power supply	= 12-24 V/1.5 A
Dimensions	200 x 56 x 125 mm (dimensions of device) 178 x 48 x 112 mm (mounting dimensions)
Weight	724 g

  
DC IN

  
FUSE

  
SPEAKER OUT

  
AUX IN  
L  
R

**AKB-160**

Order No. 0174260

**100V****PA amplifier module, with 100 V output.**

- 1 x 40 W
- Silent operation due to fanless cooling concept
- Balanced line input (XLR) and unbalanced line input (RCA)
- Speaker output via screw terminal
- Volume control
- Metal housing with mounting brackets

Model	AKB-160
Peak output power	60 W
Power rating at 100 V	40 W
Inputs	390 mV/26 kΩ, bal. 420 mV/11 kΩ, unbal.
Frequency range	17-20,000 Hz
S/N ratio	> 80 dB
THD	< 1%
Power supply	~ 230 V/50 Hz/75 VA
Dimensions	213 x 55 x 238 mm
Weight	3.2 kg

**PROFESSIONAL  
AUDIO OVER IP  
SOLUTIONS****MONACOR-DT, practically  
shaping up for the future ...**

Thanks to the DT series, Audio over IP solutions with Dante® interfaces can now conveniently be implemented at a very attractive price. Taking centre stage is the speaker **WALL-05DTM**.

**MADE IN GERMANY**  
by MONACOR

**MONACOR**

Your Project is Our Project