

## Tender text

### PA-302

#### Mono PA mixing amplifier,

14 W.

- 1 microphone input and 1 line input, adjustable
- 2 speaker outputs, switchable
- Built-in speaker
- Can also be operated as an intercom system
- Supplied with hand-held push-to-talk microphone
- Siren and fog horn, automatic fog horn
- Metal housing
- Supplied with mounting brackets
- 12/24 V battery operation, automatic switching

#### Specifications:

Peak output power	20 W
Power rating	14 W
Channels	2
Inputs	3 mV (mic), 50 mV (line)
Frequency range	20-20,000 Hz
S/N ratio	65 dB
THD	< 0.5%
Admiss. ambient temp.	0-40 °C
Width	175 mm
Height	60 mm
Depth	170 mm
Weight	1.4 kg
Connections	1 x 6.3 mm jack (mic input), 1 x RCA (line input), 2 x 2-pole plug-in screw terminal (speakers), 1 x 3-pole plug-in screw terminal with jumper (external speakers)
Packing dimensions (W x H x L)	0.23 x 0.1 x 0.3 m
Gross weight	1.84 kg
Net weight	1.41 kg

Brand: MONACOR

Type: PA-302

Quantity: 1

Packing dimensions (W x H x L): 0.23 x 0.1 x 0.3 m

Gross weight: 1.84 kg

Net weight: 1.41 kg

Item weight (w/o accessories): 1.4 kg