

Tender text

TXA-802MT

Multifrequency transmitter module,

with UHF PLL technology.

For retrofitting amplifier systems of the TXA-800 and TXA-1000 series or for setting up wireless audio transmission paths.

- 16 selectable UHF frequencies (863.1-864.9 MHz)
- Volume control
- LCD for indicating selected channel/frequency
- LEDs for indicating carrier signal and audio signal
- Power supply: DC 12 V/120 mA

Licence-free in the EU.

Specifications:

General information

Description	multifrequency transmitter module
Carrier frequency range	863.1-864.9 MHz
Channels	1
Admiss. ambient temp.	0-40 °C
Specifications transmitter	
Transmitting power	≤ 10 mW
Operating range	approx. 30 m
Power supply transmitter	DC 12 V/120 mA
Width transmitter	191 mm
Height transmitter	43 mm
Depth transmitter	110 mm
Weight transmitter	230 g

Brand: MONACOR

Type: TXA-802MT

Quantity: 1

Packing dimensions (W x H x L): 0.13 x 0.055 x 0.24 m

Gross weight: 0.315 kg

Net weight: 0.23 kg

Item weight (w/o accessories): 0.23 kg