



FGA-22HQ

Order No.: 0066370

PRODUCTINFOS

High-end transformer,

for connecting speaker outputs of a car radio to the line inputs of an amplifier.

- Internal ground separation
- Adjustable output level
- Screw terminals, gold-plated RCA jacks
- Max. input power: 20 W
- Input/output impedance: 45 Ω /30 Ω -2.8 k Ω
- Frequency range: 20-30,000 Hz
- THD: < 0.001%
- 42 x 29 x 96 mm, 104 g

TECHNICAL SPECIFICATIONS

FGA-22HQ

Description	transformer
Frequency range	20-30,000 Hz

FGA-22HQ

Input impedance	45 Ω
Output impedance	30 Ω -2.8 k Ω
THD	< 0.001%
Admiss. ambient temp.	0-40 °C
Dimensions	42 x 29 x 96 mm
Weight	104 g
Inputs	screw terminals
Outputs	1 x RCA L/R