



TXA-800HSE

Order No.: 0172250

PRODUCTINFOS

Multifrequency pocket transmitter,

with UHF PLL technology. Matching portable amplifier systems of the TXA-1000 series, TXA-800 series and TXA-800R.

- 1 headband microphone (omnidir. char.), 1 tie clip microphone (cardioid char.)
- 16 selectable UHF frequencies (863.1-864.9 MHz)
- Metal housing
- Microphone connection via 3-pole mini XLR jack
- Audio line input via 3.5 mm stereo jack
- Sensitivity to be adjusted in 3 steps
- Mute function
- Backlit LCD for indicating channel/frequency and battery status
- Transmitting power: 10 mW (EIRP)
- Power supply via 2 x 1.5 V battery AA size (not supplied)
- Belt clip

Licence-free in the EU.

tastenwelt 02/2008

“The use of the headset is interesting for keyboard players.”

TECHNICAL SPECIFICATIONS

TXA-800HSE

General information

	-
Description	pocket transmitter
Carrier frequency range	863.1-864.9 MHz
Audio frequency range	70-16,000 Hz
Channels	1
Admiss. ambient temp.	0-40 °C

Specifications transmitter

	-
Transmitting power	10 mW
Operating range	30 m
Power supply transmitter	2 x 1.5 V batt. AA size
Width transmitter	65 mm
Height transmitter	95 mm
Depth transmitter	30 mm
Weight transmitter	110 g
Connections transmitter	1 x 3-pole mini XLR