



## PATL-105

Order No.: 1000266

### PRODUCTINFOS

#### 5-way 100 V transformer,

for connecting a 100 V audio signal source to devices with line inputs.

- Suitable for PA mixing amplifiers PA-1120, PA-1240, PA-6240, PA-6480, PA-6000
- Transforming 100 V output signals into line signals to 5 lines (galvanically isolated)
- To be mounted directly to the rear panel of a respective amplifier
- Frequency range: 15-30,000 Hz
- Dimensions: 120 x 75 x 60 mm
- Weight: 405 g

### TECHNICAL SPECIFICATIONS

#### PATL-105

|                  |                   |
|------------------|-------------------|
| Description      | 100 V transformer |
| Frequency range  | 15-30,000 Hz      |
| Input impedance  | 20 k $\Omega$     |
| Output impedance | 200 $\Omega$      |

**PATL-105**

|                       |                  |
|-----------------------|------------------|
| Admiss. ambient temp. | 0-40 °C          |
| Dimensions            | 120 x 75 x 60 mm |
| Weight                | 405 g            |
| Inputs                | cable lugs       |
| Outputs               | screw terminals  |