



PATL-105

Order No.: 1000266

PRODUCTINFOS

5-way 100 V transformer,

for connecting a 100 V audio signal source to devices with line inputs.

- Suitable for PA mixing amplifiers PA-1120, PA-1240, PA-6240, PA-6480, PA-6000
- Transforming 100 V output signals into line signals to 5 lines (galvanically isolated)
- To be mounted directly to the rear panel of a respective amplifier
- Frequency range: 15-30,000 Hz
- Dimensions: 120 x 75 x 60 mm
- Weight: 405 g

TECHNICAL SPECIFICATIONS

PATL-105

Description	100 V transformer
Frequency range	15-30,000 Hz
Input impedance	20 k Ω
Output impedance	200 Ω

PATL-105

Admiss. ambient temp.	0-40 °C
Dimensions	120 x 75 x 60 mm
Weight	405 g
Inputs	cable lugs
Outputs	screw terminals